



JDYX8.E156471

Fuses, Supplemental Certified for Canada - Component

[Page Bottom](#)

Fuses, Supplemental Certified for Canada - Component

[See General Information for Fuses, Supplemental Certified for Canada - Component](#)

HOLLYLAND CO LTD

E156471

UNIT B, 31ST FL

BILLION CENTRE, TOWER A

1 WANG KWONG RD

KOWLOON BAY, KOWLOON HONG KONG

Supplemental fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
41S	4.5 x 15 (0.18 x 0.59)	4 - 10	125Vac	100
		4 - 10	250Vac	100
50CT	5.2 x 20 (0.20 x 0.79)	0.2 - 0.63	250Vac	200, 1500
		0.8 - 1.0	250Vac	200, 1500
		1.25 - 15	250Vac	200, 1500
50F	5.2 x 20 (0.20 x 0.79)	0.2 - 0.8	250Vac	35
		1.0 - 3.15	250Vac	35
		4.0 - 6.3	250Vac	10x Ampere rating
		8 - 16	250Vac	10x Ampere rating
50T	5.2 x 20 (0.20 x 0.79)	0.125 - 0.4	250Vac	35
		0.5 - 3.15	250Vac	35
		4.0 - 6.3	250Vac	10x Ampere rating
		8 - 15	250Vac	63
65NM	6.35 x 31.8 (0.25 x 1.25)	20 - 30	125Vac	100
		20 - 30	250Vac	100
		20 - 30	125Vdc	400
		20 - 30	300Vac	1000

Supplemental fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
42S,41S(P)	4.5 x 15 (0.18 x 0.59)	4 - 10	125Vac	100
		4 - 10	250Vac	100
50CT(P)	5.2 x 20 (0.20 x 0.79)	0.2 - 0.63	250Vac	200, 1500
		0.8 - 1.0	250Vac	200, 1500
		1.25 - 15	250Vac	200, 1500
50F(P)	5.2 x 20	0.2 - 0.8	250Vac	35

	(0.20 x 0.79)			
		1.0 - 3.15	250Vac	35
		4.0 - 6.3	250Vac	10x Ampere rating
		8 - 16	250Vac	10x Ampere rating
50T(P)	5.2 x 20 (0.20 x 0.79)	0.125 - 0.4	250Vac	35
		0.5 - 3.15	250Vac	35
		4.0 - 6.3	250Vac	10x Ampere rating
		8 - 15	250Vac	63
5GT	5.0 x 20 (0.20 x 0.79)	0.8 - 3.5	250Vac	35
		4 - 6.3	250Vac	63
		7 - 10	250Vac	100
61NM(P)	6.85 x 32.4 (0.27 x 1.28)	12 - 30	32Vac	300
		12 - 30	32Vdc	300
62NM	6.85 x 32.4 (0.27 x 1.28)	12 - 30	32Vac	300
		12 - 30	32Vdc	300

Supplemental fuses: pigtail leads, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
41NM(P)	3.9 x 13.7 (0.15 x 0.54)	0.3 - 2.25	300Vac	50
		0.3 - 2.25	125Vac	500
		2.5 - 5.0	300Vac	50
		2.5 - 5.0	250Vac	100
		2.5 - 5.0	125Vac	500
		0.3 - 2.25	250Vac	50
41NM(P) (15A)	3.9 x 14 (0.15 x 0.55)	15	300Vac	100
65TS(P)	5.7 x 30.8 (0.22 x 1.21)	20 - 30	125Vac	400
		20 - 30	250Vac	100

Supplemental fuses: pigtail leads, filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
50CF(P)	5.6 x 21 (0.22 x 0.83)	0.25 - 2.0	250Vac	1500
		0.25 - 2.0	250Vdc	1000
		2.5 - 6.3	250Vac	1500
		2.5 - 6.3	250Vdc	1000
		8 - 16	250Vac	1500
		8 - 16	250Vdc	1000
5CT	5.2 x 20 (0.20 x 0.79)	1 - 2	250Vac	1500
		2.5 - 3.15	250Vac	1500
		3.5 - 6.3	250Vac	1500
		7.0 - 10	250Vac	1500

5HF(P)	5.55 x 21.0 (0.22 x 0.83)	0.25 - 20	300Vac	1500
		0.25 - 3.15	500Vac	1000
		4 - 20	500Vac	200
		0.25 - 20	600Vac	100
		0.25 - 20	300Vdc	1500
		0.25 - 3.15	450Vdc	1500
		4 - 20	450Vdc	400
5HT(P)	5.55 x 21.0 (0.22 x 0.83)	2 - 16	500Vac	200
		2 - 16	600Vac	100
		2 - 3.15	400Vdc	1500
		3.5 - 10	400Vdc	500
		12 - 16	400Vdc	400
65NM(P)	6.35 x 31.8 (0.25 x 1.25)	20 - 30	125Vac	100
		20 - 30	250Vac	100
		20 - 30	125Vdc	400
		20 - 30	300Vac	1000
6FF(P)	6.85 x 32.4 (0.27 x 1.28)	0.2 - 0.375	1000Vac	10000
		0.2 - 0.375	1000Vdc	10000
		0.4 - 2.0	1000Vac	10000
		0.4 - 2.0	1000Vdc	10000
6FF(P)-1	6.85 x 32.4 (0.27 x 1.28)	0.2 - 0.375	500Vac	10000
		0.2 - 0.375	500Vdc	10000
		0.4 - 2.0	500Vac	10000
		0.4 - 2.0	500Vdc	10000

Supplemental fuses: cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
41NM	3.9 x 13.7 (0.15 x 0.54)	0.3 - 2.25	250Vac	50
		0.3 - 2.25	300Vac	50
		0.3 - 2.25	125Vac	500
		2.5 - 5	300Vac	50
		2.5 - 5	250Vac	100
		2.5 - 5	125Vac	500
41NM (15A)	3.9 x 14 (0.15 x 0.55)	15	300Vac	100
61NM	6.35 x 31.8 (0.25 x 1.25)	12 - 30	32Vac	300
		12 - 30	32Vdc	300
65TS	5.7 x 30.8 (0.22 x 1.21)	20 - 25	125Vac	400
		20 - 25	250Vac	100

Supplemental fuses: filled-tube

	Size	Amps	Volts	Interrupting Rating
--	------	------	-------	---------------------

Cat. No.	mm(in)	(A)	(V)	(A)
50CF	5.2 x 20 (0.20 x 0.79)	0.25 - 2.0	250Vdc	1000
		0.25 - 2.0	250Vac	1500
		2.5 - 6.3	250Vac	1500
		2.5 - 6.3	250Vdc	1000
		8 - 16	250Vac	1500
		8 - 16	250Vdc	1000
5HF	5.25 x 20.0 (0.21 x 0.79)	0.25 - 20	300Vac	1500
		0.25 - 3.15	500Vac	1000
		4 - 20	500Vac	200
		0.25 - 20	600Vac	100
		0.25 - 20	300Vdc	1500
		0.25 - 3.15	450Vdc	1500
5HT	5.25 x 20.0 (0.21 x 0.79)	2 - 16	500Vac	200
		2 - 16	600Vac	100
		2 - 3.15	400Vdc	1500
		3.5 - 10	400Vdc	500
		12 - 16	400Vdc	400
		0.25 - 20	300Vdc	1500
6FF	6.35 x 31.8 (0.25 x 1.25)	0.2 - 0.375	1000Vac	10000
		0.4 - 2.0	1000Vac	10000
		0.4 - 2.0	1000Vdc	10000
		0.2 - 0.375	1000Vdc	10000
6FF-1	6.35 x 31.8 (0.25 x 1.25)	0.4 - 2	500Vac	10000
		0.4 - 2	500Vdc	10000
		0.2 - 0.375	500Vac	10000
		0.2 - 0.375	500Vdc	10000
HC10aR	10.3 x 38 (0.41 x 1.50)	4.0 - 6.3	500Vac	120000
		4.0 - 6.3	500Vdc	120000
		4.0 - 6.3	690Vac	80000
		4.0 - 6.3	690Vdc	50000
		4.0 - 6.3	1000Vdc	30000
		4.0 - 6.3	1000Vac	50000
		7.0 - 32	500Vac	120000
		7.0 - 32	500Vdc	120000
		7.0 - 32	690Vac	80000
		7.0 - 32	690Vdc	50000
		7.0 - 32	1000Vdc	30000
		7.0 - 32	1000Vac	50000
		0.25 - 3.15	500Vac	120000
		0.25 - 3.15	500Vdc	120000
		0.25 - 3.15	690Vac	80000
		0.25 - 3.15	690Vdc	50000

		0.25 - 3.15	1000Vdc	30000
		0.25 - 3.15	1000Vac	50000
HC10aR (silver element)				
	10.3 x 38 (0.41 x 1.50)	7 - 16	1000Vac	50000
HC10aR-B	10.3 x 38 (0.41 x 1.50)	10	500Vac	120000
		10	500Vdc	120000
		10	690Vac	80000
		10	690Vdc	50000
		10	1000Vac	50000

Supplemental micro fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
06F	1.6 x 0.85 x 0.5 (0.06 x 0.03 x 0.02)	0.1 - 0.25	32Vac	50
		0.1 - 0.25	63Vdc	50
		0.3 - 1.0	32Vac	50
		0.3 - 1.0	32Vdc	50
		1.2 - 5.0	32Vdc	35
		1.2 - 5.0	32Vac	35
06T	1.6 x 0.85 x 0.5 (0.06 x 0.03 x 0.02)	0.1 - 0.25	32Vac	50
		0.1 - 0.25	63Vdc	50
		0.3 - 1.0	32Vac	50
		0.3 - 1.0	32Vdc	50
		1.2 - 5.0	32Vdc	35
		1.2 - 5.0	32Vac	35
12F	3.2 x 1.6 x 1.0 (0.13 x 0.06 x 0.04)	0.1 - 0.375	32Vac	50
		0.1 - 0.375	63Vdc	50
		0.4 - 3.0	63Vac	50
		0.4 - 3.0	63Vdc	50
		3.15 - 7	24Vac	35
		3.15 - 7	32Vdc	50
12T	3.2 x 1.6 x 1.0 (0.13 x 0.06 x 0.04)	0.1 - 0.375	63Vac	50
		0.1 - 0.375	63Vdc	50
		0.4 - 3.0	63Vac	50
		0.4 - 3.0	63Vdc	50
		3.15 - 7	24Vac	35
		3.15 - 7	32Vdc	50
20N	2.42 x 7.1 (0.10 x 0.28)	3.15 - 10	125Vac	30
		3.15 - 10	250Vac	30
		3.15 - 10	125Vdc	50
		0.1 - 0.315	250Vac	30
		0.1 - 0.315	125Vdc	50
		12 - 15	72Vac	30

		20	60Vdc	50
		15 - 20	32Vdc	300
20T	2.42 x 7.1 (0.10 x 0.28)	0.1 - 7	125Vac	30
		0.1 - 7	250Vac	30
2N0100L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.1	125Vac	50
2N010L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	1	125Vac	50
2N0125L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.125	125Vac	50
2N013L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	1.25	125Vac	50
2N015L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	1.5	125Vac	50
2N0160L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.16	125Vac	50
2N016L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	1.6	125Vac	50
2N0200L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.2	125Vac	50
2N020L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	2	125Vac	50
2N0250L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.25	125Vac	50
2N025L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	2.5	125Vac	50
2N030L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	3	125Vac	50
2N0315L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.315	125Vac	50
2N032L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	3.15	125Vac	50
2N035L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	3.5	125Vac	50
2N0375L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.375	125Vac	50
2N0400L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.4	125Vac	50
2N040L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	4	125Vac	50
2N0500L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.5	125Vac	50
2N050L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	5	125Vac	50
2N0630L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.63	125Vac	50
2N063L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	6.3	125Vac	50
2N070L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	7	125Vac	50
2N0750L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.75	125Vac	50
2N0800L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	0.8	125Vac	50
2N080L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	8	125Vac	50
2N100L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	10	125Vac	50
2N120L	5.7 x 2.2 x 2.2	12	65Vac	50

	(0.22 x 0.09 x 0.09)			
2N150L	5.7 x 2.2 x 2.2 (0.22 x 0.09 x 0.09)	15	65Vac	50

Supplemental micro fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
30TS	4.0 x 9.0 (0.16 x 0.35)	0.2 - 1.6	350Vac	30
5RF	8.3 x 7.8 x 2.2 (0.33 x 0.31 x 0.09)	0.315 - 2.5	250Vac	35
		3.15	250Vac	35
		4	250Vac	40
		5	250Vac	50
		6.3	250Vac	63

Supplemental micro fuses: pigtail leads, filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
25S	3.6 x 10.0 (0.14 x 0.39)	1 - 2	125Vac	50
		1 - 2	250Vac	50
5EF	8.5 x 8.3 x 4 (0.33 x 0.33 x 0.16)	0.315 - 2.5	250Vac	35
		3.15	250Vac	35
		4	250Vac	40
		5	250Vac	50
		6.3	250Vac	63

Supplemental micro fuses: filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
5ET	8.0 x 4.0 x 8.5 (0.31 x 0.16 x 0.33)	0.1 - 0.25	300Vac	50
		0.1 - 0.25	125Vdc	50
		0.315 - 5	125Vdc	50
		0.315 - 5	250Vac	63
		0.315 - 5	300Vac	50
		6.3	300Vac	50
		6.3	250Vac	63
		6.3	125Vdc	63
		0.315 - 10	250Vac	130
5RT	8.3 x 7.5 (0.33 x 0.30)	0.1 - 0.25	300Vac	50
		0.1 - 0.25	125Vdc	50
		0.315 - 5.0	300Vac	50
		0.315 - 5.0	250Vac	63
		0.315 - 5.0	125Vdc	50
		6.3	300Vac	50
		6.3	250Vac	63
		6.3	125Vdc	63

Supplemental micro fuses: surface mount

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
0603FT	1.6 x 0.8 x 0.5 (0.06 x 0.03 x 0.02)	0.25 - 5	50Vdc	35
0805FT	2 x 1.5 x 0.57 (0.08 x 0.06 x 0.02)	0.4 - 5	50Vdc	50
1206FT	1.6 x 0.8 x 0.5 (0.06 x 0.03 x 0.02)	0.5 - 2	63Vdc	50
		2.5 - 7	32Vdc	50
		2.5 - 7	63Vdc	50
		0.5 - 4	76Vdc	50
25F	6.2 x 2.65 x 2.65 (0.24 x 0.10 x 0.10)	0.1 - 5	125Vac	100
		0.1 - 5	125Vdc	100
		0.1 - 5	250Vac	50
		6 - 10	125Vac	100
		6 - 10	125Vdc	100
		6 - 10	250Vac	50
		11 - 15	125Vac	50
		11 - 15	125Vdc	50
		11 - 15	65Vdc	100
25T	6.2 x 2.65 x 2.65 (0.24 x 0.10 x 0.10)	0.2 - 1	125Vac	100
		0.2 - 1	250Vac	50
		0.2 - 1	125Vdc	100
		1.2 - 5	125Vac	100
		1.2 - 5	125Vdc	100
		1.2 - 5	250Vac	50

(P) - Pigtail leads.

Note - The following models are identical to each other except for the model numbers: 41NM(P) and 42NM; 51NM(P) and 52NM; 51MS(P) and 52MS.



Marking: Company name or tradename "H in a circle", "HOLLY", model designation and the Recognized Component Mark for Canada,

Last Updated on 2015-05-08

[Questions?](#)

[Print this page](#)

[Terms of Use](#)

[Page Top](#)

?2015 UL LLC

When the UL Leaf Mark is on the product, or when the word "Environment" is included in the UL Mark, please search the [UL Environment database](#) for additional information regarding this product's certification.

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2015 UL LLC".